








## REPLENISH NMD-50 CASSETTE(S)



STEP	ACTION
1	<p>UNLOCK/OPEN DISPENSER SECURITY DOOR. GRASP CASSETTE HANDLE WITH ONE HAND WHILE HOLDING MECHANISM WITH THE OTHER.</p> <p>PULL CASSETTE OUT SLIGHTLY, THEN PLACE ONE HAND UNDERNEATH. REMOVE CASSETTE.</p> 
2	<p>PRESS THE GREEN RELEASE BUTTON AND LIFT THE LID. FLIP THE LID BACK FULLY LETTING IT REST ON A FLAT SURFACE.</p> 
3	<p>MOVE THE PACKER PLATE TOWARDS THE REAR.</p> 
4	<p>COUNT THE NUMBER OF BILLS THAT REMAIN IN THE CASSETTE, IF ANY.</p> <p>COUNT THE NUMBER OF BILLS THAT ARE BEING ADDED TO THE REMAINING NOTES.</p> <p>THE <b>TOTAL</b> OF THESE AMOUNTS WILL BE ENTERED IN THE "ENTER CASSETTE QUANTITY" PROMPT FOR CASSETTE CLOSE PROCEDURE.</p>

STEP	ACTION
5	<p>PLACE CURRENCY IN THE CASSETTE AND MOVE PACKER PLATE AGAINST THE NOTES.</p> 
6	<p>EXTEND THE "PAWLS" ON PACKER PLATE FULLY. CLOSE LID AND INSTALL IN DISPENSER.</p> 
7	<p>REMOVE REJECT VAULT.</p> <p>OPEN VAULT BY ROTATING GREEN RELEASE LEVER "COUNTERCLOCKWISE". GRASP LID AND OPEN. REMOVE ANY REJECTED NOTES. <b>DO NOT RECYCLE REJECTED NOTES!</b></p>  <p>ROTATE GREEN RELEASE LEVER AGAIN AND CLOSE LID. INSTALL REJECT VAULT IN DISPENSER.</p> 

For more information or assistance, please call **cashline** 1-888-870-9780